

## Auto-Provisioning an IP550

- Go to PBX setup->General and turn on Auto-Provisioning

**Admin Settings**

Admin User Name	<input type="text" value="pbxadmin"/>	?
Admin password	<input type="password" value="....."/>	?
Re-type Admin password	<input type="password" value="....."/>	?

**General Settings**

Timezone	<input type="text" value="Eastern"/>	?
System Operator	<input type="text" value="None"/>	?
Mailbox Exit Destination	<input type="text" value="None"/>	?
Directory Type	<input type="text" value="Last Name"/>	
Default Class of Service	<input type="text" value="System Default"/>	
Branch Class of Service	<input type="text" value="System Default"/>	
Internal Distinctive Ring	<input type="text" value="Default"/>	
Auto-Provisioning:	<input type="button" value="On"/> <input type="button" value="Off"/>	
	Running	

- Create an extension and under Advanced set the phone type to IPitomy 550

Advanced Settings	
Network Settings	Voicemail Settings
SIP Password: <input type="text" value="jU8yg9"/> <input type="button" value="Generate"/>	Mailbox: <input type="text" value="2217"/>
Location: <input type="text" value="LAN (Local)"/> ▼	Attach to Email: Yes <input checked="" type="radio"/> No <input type="radio"/> N/A <input type="radio"/>
NAT: <input checked="" type="checkbox"/>	Delete After Emailing: Yes <input type="radio"/> No <input checked="" type="radio"/> N/A <input type="radio"/>
Host: <input type="text" value="dynamic"/>	Turn Old After Emailing: Yes <input type="radio"/> No <input checked="" type="radio"/>
Phone Type: <input type="text" value="IPitomy 550"/> ▼ <a href="#">Settings</a>	Say Caller ID: Yes <input checked="" type="radio"/> No <input type="radio"/> N/A <input type="radio"/>
Phone MAC: <input type="text" value="00C0020FBCE1"/>	Allow Review: Yes <input type="radio"/> No <input checked="" type="radio"/> N/A <input type="radio"/>
Qualify: <input type="text" value="8000"/>	Allow Operator: Yes <input checked="" type="radio"/> No <input type="radio"/> N/A <input type="radio"/>
DTMF Mode: <input type="text" value="info"/> ▼	Play Envelope Message: Yes <input checked="" type="radio"/> No <input type="radio"/> N/A <input type="radio"/>
User Type: <input type="text" value="Friend"/> ▼	Auto Delete Voicemail in: <input type="text" value="90"/> days
Call Limit: <input type="text" value="99"/> ?	
Can Reinvite: <input type="radio"/> Yes <input type="radio"/> No <input checked="" type="radio"/> N/A	
Insecure: <input type="text" value="Very"/> ▼	
MusicOnHold: <input type="text" value="Use System Default"/> ▼	

- On the phone press Menu followed by 7
- Enter the password (1234) followed by the Enter softkey
- Press 8
- Select YES for Auto PBX Search
- Enter the extension number of the extension that was just created followed by the Done softkey
- The phone should display Ext. No. Authorized and begin provisioning the phone. Once finished, the phone will be registered with the PBX.

## Manually Configuring an IP550

- Connect power to the phone, and the phone to your network
- Press Menu, press 8, press 1 and note the IP address.
- Enter the IP address into a web browser (user: admin/password: 1234)
- Navigate to Line 1 thru 4 and enter the following data, saving on each screen before you advance to the next line
  - Screen Name: Any value
  - Phone Number: Extension Number
  - Authentication Name: Extension Number
  - Password: SIP Password for the extension (found by editing the extensions setting on the PBX and clicking the advanced link)
  - Proxy Server: PBX IP Address
  - Proxy Port: 5060

## Configuration Line 1

### Basic SIP Authentication Settings

Screen Name	Mike Lunn
Phone Number	2217
Authentication Name	2217
Password	jU8yg9

### Basic SIP Network Settings

Proxy Server	192.168.2.18
Proxy Port	5060
Backup Proxy Server	
Backup Proxy Port	5060
Outbound Proxy Server	
Outbound Proxy Port	5082
Registration Period	3600

Save

- Navigate to Reset and click Restart
- Once the phone finishes rebooting, all 4 lines will be configured to the same extension, allowing 4 concurrent calls on the phone